



???????????? ??????????

??????	HY103	HY203	HY503	HY1002	HY3002	HY5002	
?????? ???????	100	200	500	1000	3000	5000	mm
???????? ???????	0.001	0.002	0.005	0.02	0.05	0.05	mm
?????? ???????????	0.001	0.002	0.01	0.02	0.05	0.05	mm
????????	0.002	0.004	0.01	0.02	0.05	0.10	mm
???????????????? ??????	0.003	0.006	0.02	0.04	0.08	0.20	mm
?????? ?????????	100 x 100		300 x 300				mm
????? ?????????????	0.2~0.4 s (????? ?? ????????? ?? ?????? ????????? ???), ?????? ?????????? AD 350 ??						
????????	24 VDC ± 15% ?<2 W						
?????????? 1	RS232+RS485?Modbus RTU, ???????????						
?????????? 2	Ethernet ????????????, Modbus TCP						
????????? ????	????????????????? ?????????, 10~24 ? ??????????? ???, 5 ??						
????????? ????	????????????????? ?????????, 10~24 ? ??????????? ???, 0.25A						
????? ??????	IP54						
???????? ??????	+10°C ~ +40°C, ?????????<80% RH, ??? ???????????						
?????????? ???????????	???????? ????????????????? ??????, ????? 3 ?, ????????????? ?????? (?????)						
????????? ???????	RD	+24VDC		BK	GND		
RS232	OG	TXD		YL	RXD		
	GY	COM					
RS485	PK	485A		BN	485B		
2DI	GN	IN1 Dynamic and static		PL	IN2 weighing in place		
4DO	WT	OUT1 (too light)		RDWT	OUT2 (qualified)		
	BNWT	OUT3 (overweight)		BKWT	OUT4 (alarm)		